

# FLASHER

PROGRAMMABLE

2 HIGH CURRENT MOSFET  
OUTPUTS AVAILABLE-NEGATIVE  
POLARITY

MULTIVOLTAGE 10-30V



## Specifications

<b>Power supply</b>	12 V or 24 V DC, -10 +15%
<b>Power consumption*</b>	approx. 2 W
<b>Number of outputs</b>	2 x factory programmable relay output
<b>Relay output</b>	max.1 A
<b>Electrical connection</b>	2,8 x 0,8 flat connector
<b>Enclosure protection (IEC 529)</b>	IP20
<b>Operating temperature</b>	from -45 °C to +85 °C
<b>Dimensions</b>	65 x 60 x 27 mm
<b>Weight</b>	80 g

\*No outputs active

Flasher is an electronic device with two output signals which can control blinking lamps mounted near the left and right front and rear corners of a vehicle, and also on the open steps, if mounted on each side of the vehicle. The Flasher can be activated by the driver or automatically by opening the side steps.